

Analog Multimeter

Model No.: **KT7008/1015B Analog Multimeter**



- Analogue multimeter in a handy compact housing
- 16 ranges in 6 functions
- AC/DC voltage measurement up to 500V
- DC current measurement up to 250mA
- Resistance measurement up to 2M Ω
- Battery test 1.5V and 9V
- Fuse: F500mA/250V
- Input impedance: 10K Ω / VDC, 4.5K Ω / VAC
- Accessories included: 1.5V battery, test leads, English manual, full blister

SPECIFICATIONS

DC Voltage	2.5/10/50/250/500V (\pm 5.0% f.s)
AC Voltage	10/50/250/500V (\pm 5.0% f.s)
DC Current	10m/250mA (\pm 4% f.s)
Resistance	20K Ω (Rx10)/2M Ω (Rx1K) (\pm 5.0% of full arc)
Battery test	1.5V (250mA), 9V (10mA)
dB measurement:	-22~20 (0dB 1mW/600 Ω)
Operating temperature	0~40 $^{\circ}$ C (32~104 $^{\circ}$ F) at RH<80%
Dimensions	116x68x35mm
Weight	Approx. 195g included battery
Measurement Category	EN61010-1,CAT II,300V

